MICROMOTORS | CORELESS BLDC MOTORS | SVTN A 01-2864-36-D-O



Coreless BLDC motor.

High Power Density - High Efficiency - Cost Effective Low noise - Low inductance - Good Heat Dissipation Long Lifetime - No Cogging - Low Inertia - Robust

Feature

	SVTN A 01-2864-36-D-O
Nominal voltage	36 V
No load speed	8275 rpm
No load current	92 mA
Nominal speed	7053 rpm
Nominal torque	50.000 mNm
Nominal current	1.310 A
Stall torque	339.000 mNm
Stall current	8.300 A
Max. efficiency	80.100 %
Terminal resistance*	4.300 Ω
Terminal inductance*	0.960 mH
Torque constant	41.090 mNm/A
Speed constant	232 mNm/V

Notice: The provided technical data are the higher limits recommended in static condition. To obtain the correct dimensioning of the product, it is necessary to hold account of all the applicable dynamic forces, including the inertia of the manipulator, the configuration of the tools and the external forces applied.

2 POLE BRUSHLESS DC MOTORS

	SVTN A 01-2864-36-D-O
Speed/torque gradient	24.40 rpm/mNm
Mechanical time constant	2.500 ms
Rotor inertia	9.620 gcm²

The benefits of this new technology are torque and high-speed when compared to the same sizing. The lack of cogging, a reduced ripple torque, a linear correlation between speed and torque, low inertia bring performance to a greater level in terms of power, dynamics by means of reduced weights and reduced dimensions. Servotecnica's brushless motors apply hall sensors as a standard option, in addition to having the magnetic encoder option. Thanks to the sensors it is possible to control rotation speed, and, thanks to the lack of cogging, provide high performance and accuracy.





Winding technology without metal bodies

Good heat dissipation and high overload

Long life expectancy

Light and compact, easy integration

High reliability

Good return on investment

